

# Wireless Pull Cord

Easily installed, a wireless pull cord will trigger a call on a home unit to staff or to a remote monitoring service.

A pull cord is an essential requirement for times when a personal activator may not be worn, such as in the bedroom or bathroom, giving the user an extra means of raising an alarm.

The wireless pull cord requires extremely low maintenance with battery life of typically 10 years.

## Features

- Red cord with small white end grip
- Momentary action pull switch
- 4 hour supervision transmission
- Automatic low battery reporting
- Battery isolation switch for transportation



# Technical Details

|                       |   |
|-----------------------|---|
| Part Number           | 64604/02  |
| Fixing Details        | Fitting into a wall box with faceplate mounting on 3.3" centers   |
| Radio Frequency       | 312.000 MHz   |
| Battery               | <ul style="list-style-type: none"><li>• Integral battery, not user replaceable</li><li>• The battery has a typical life of 10 years, or 80,000 transmissions (included supervision transmissions) whichever is sooner</li></ul> |
| Dimensions            | W 2.76" x H 4.49" x D 2.99" (70mm x 80mm x 23mm)  |
| Cord Length           | 4'2" (122.5cm)  |
| Operating Temp Range  | 14° F to 131° F (-10° C to 55° C)   |
| Radio Range           | 300 ft to 450 ft (91 m to 137 m) in free space.   |
| Supervision           | Full  |
| Standards             | FCC CFR47 part 15, Canadian RSS210  |
| Product Compatibility | Caresse+ and Vi+  |

Tunstall Canada Inc.  
111 Zenway Blvd, Unit 6A  
Woodbridge, Ontario  
Canada L4H 3H9

Tel: 1-800-892-2205  
Tel: 905-677-1144  
Email: [info.canada@tunstall.com](mailto:info.canada@tunstall.com)  
[canada.tunstall.com](http://canada.tunstall.com)  
[americas.tunstall.com](http://americas.tunstall.com)